

Installation Instructions Connector Attachment

For Braided Cable CNT-300
N Female, Captivated Pin,
Crimp-type Body: 300PNF-C-CR



1 Remove 18.0 mm (0.709") of Jacket only.

2 Trim 8.5 mm (0.335") of braid, exposing foam.

3 Remove 6.0 mm (0.236") of foam, exposing center conductor.

4 Chamfer the center conductor at a 45° angle.

5 Slide part A onto cable, splay out braid as shown.

6 The cable attachment must be straight and aligned with the hole of connector inner contact. Insert cable attachment into connector body until stopped; the cable center conductor must be inserted into inner contact hole. Make sure the braid cover on body sleeve and push part A onto braid.

7 Crimp part A at the area as shown. Crimp tool part number is: CTBC.



	表一 有毒有害物质或元素名称及含量标识格式					
	有毒有害物质或元素					
部件名称 (Part Name)	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr6+)	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
连接器 (Connector)	X	O	O	O	O	O

O: 表示有毒有害物质在该部件所有的均质材料中的含量均在SJ/T 11363-2006规定的限量要求以下。
X: 表示该有毒有害物质至少在该部件的某一均质材料中的含量超出SJ/T 11363-2006规定的限量要求。



Installation Training Available at Andrew Institute

Notice: Andrew disclaims any liability or responsibility for the results of improper or unsafe installation, in spection, maintenance, or removal practices

Andrew Corporation
3 Westbrook Corporate Center, Suite 900, Westchester, Illinois U.S.A. 60154
+1 (779) 435-8579 Fax (U.S.A.): 1-800-349-5444
www.andrew.com
Copyright © 2007 by Andrew Corporation

Customer Service, 24 hours
U.S.A., Canada, Mexico: 1-800-255-1479
U.K.: 0800 250055
Other Europe: +44 592 782 612
China: +86 512-6256-8805